

**EVOCARE CONTACT:**

Sales: 07 3355 8000

Fax: 07 3355 5043

Email: [sales@evocare.com.au](mailto:sales@evocare.com.au)

PO Box 1144, Stafford

Q 4053 Australia

# LMT6 – TENS & EMS

**Call or email for more information**



Side View

## LMT6 - Digital TENS (*Transcutaneous electrical nerve stimulation*) and EMS (*Electric Muscle Stimulation*) with Soft Bag



### Technical Specifications

<b>Digital Buttons:</b>	Control EMS and TENS modes with large LCD display.
<b>Dual Channel:</b>	Isolated between channels.
<b>Modes:</b>	3 TENS and 3 EMS
<b>Pulse Rate:</b>	Adjustable. 1Hz - 150Hz
<b>Pulse Width:</b>	Adjustable. 30 – 300 microseconds
<b>Pulse Intensity:</b>	Adjustable 0-100mA peak into 500ohm load each channel
<b>Timer:</b>	5 to 95 minutes and Continuous.
<b>Wave Form:</b>	Asymmetrical Bi-phasic square pulse
<b>Ramp Time:</b>	1—20 seconds.
<b>Cycle On Time:</b>	On: 1—30 seconds, Off: 1—60 seconds.
<b>Battery:</b>	3 x AAA batteries (4.5V)
<b>Warranty:</b>	1 year

### Package contains:

- LMT4+EMS TENS unit with Belt Clip
- Carry Case
- Set of Leads
- 4 Self-adhering Electrodes 5cm x 5cm
- 4 Self-adhering Electrodes 5cm x 9cm
- 3 x AAA Batteries
- Instruction Booklet

Website Link: <http://www.evocare.com.au/tens-lmt6.php>



Top View

### Available Replacement Electrodes:

- LMTEL5090 Electrode (Pack 4) 50 x 90mm square self adhesive and pre-gelled
- LMTEL Electrode (Pack 4) 50 x 50mm square self adhesive and pre-gelled

